

Technical Information

Rechargeable Battery Life NFM-Family*



Battery life in days NFM-750 with CSM-D and one battery				
Storage Cycle [min.]	GPRS Transmission Cycle [hrs.]			
	none	24	12	6
1	38	38	38	37
2	71	70	70	69
5	145	143	142	139
10	224	220	216	209
30	350	341	332	316
60	408	396	384	363

Battery life in days NFM-600 with NIC-CO01 and one battery				
Storage Cycle [min.]	GPRS Transmission Cycle [hrs.]			
	none	24	12	6
1	58	58	58	57
2	104	103	102	101
5	197	194	191	186
10	281	275	269	258
30	392	380	370	350
60	435	421	408	384

Battery life in days NFM-050 with NMI0-06 and one battery				
Storage Cycle [min.]	GPRS Transmission Cycle [hrs.]			
	none	24	12	6
1	71	71	71	70
2	124	123	122	120
5	225	221	218	211
10	308	301	294	282
30	409	396	385	363
60	445	431	417	392

Battery life in days NFM-550 with NMI0-06 and one battery				
Storage Cycle [min.]	GPRS Transmission Cycle [hrs.]			
	none	24	12	6
1	11	11	11	10
2	21	21	21	21
5	50	49	49	49
10	90	89	89	87
30	193	190	187	181
60	271	265	259	248

Battery life in days NFM-750 with CSM-D and two batteries				
Storage Cycle [min.]	GPRS Transmission Cycle [hrs.]			
	none	24	12	6
1	73	73	73	72
2	132	131	130	129
5	252	250	248	243
10	364	359	354	345
30	516	506	496	478
60	576	564	552	529

Battery life in days NFM-600 with NIC-CO01 and two batteries				
Storage Cycle [min.]	GPRS Transmission Cycle [hrs.]			
	none	24	12	6
1	110	109	109	108
2	188	186	185	182
5	328	324	320	312
10	436	429	422	409
30	560	548	537	516
60	602	589	576	552

Battery life in days NFM-050 with NMI0-06 and two batteries				
Storage Cycle [min.]	GPRS Transmission Cycle [hrs.]			
	none	24	12	6
1	133	132	132	130
2	221	219	217	214
5	366	361	356	347
10	469	461	453	438
30	577	565	553	530
60	612	598	585	560

Battery life in days NFM-550 with NMI0-06 and two batteries				
Storage Cycle [min.]	GPRS Transmission Cycle [hrs.]			
	none	24	12	6
1	21	21	21	21
2	42	42	42	41
5	95	95	95	94
10	165	164	163	161
30	325	320	315	308
60	427	420	413	399

*Guide values under lab conditions. Battery life may vary depending on application and, among other things, depends on batch tolerances, other capacities, reception quality etc.

You can find comprehensive specifications in the respective manuals or on www.nivus.com

NIVUS GmbH
Im Täle 2
75031 Eppingen, Germany
Tel.: +49(0)7262 9191 0
Fax: +49(0)7262 9191 999
info@nivus.com

www.nivus.de

NIVUS AG
8750 Glarus, Switzerland
Tel.: +41(0)55 6452066
swiss@nivus.com

NIVUS Austria
3382 Loosdorf, Austria
Tel.: +43 (0)2754 5676321
austria@nivus.com

NIVUS Sp. z o.o.
81-212 Gdynia, Poland
Tel.: +48(0)58 7602015
biuro@nivus.pl

NIVUS France
67870 Bischoffsheim, France
Tel.: +33(0)388 99 92 84
info@nivus.fr

NIVUS Ltd.
Head office UK:
Tel. +44(0)1926632470
info-uk@nivus.com

NIVUS Middle East (FZE)
Sharjah Free Zone, UAE
Tel.: +971 6 55 78 224
middle-east@nivus.com

NIVUS Korea Co. Ltd.
Incheon, Korea 21984
Tel.: +82 32 209 8588
korea@nivus.com

NIVUS Vietnam
Hanoi
Tel.: +84 12 0446 7724
vietnam@nivus.com